



Addressable Fire Alarm Control Panels

6700

Addressable Fire Alarm Control Panel

The 6700 is an addressable fire alarm control panel (FACP) that is a direct replacement for the 5700 FACP. The 6700 can be configured to achieve a point capacity of up to 100 points. It has one built-in signaling line circuit (SLC), which can support 50 System Sensor® (SK) sensors and 50 SK modules or 50 Hochiki® (SD) devices.

A common communications and annunciation link allows up to 17 panels to be connected via copper or fiber optic cable. A designated panel is configured as the communicator for all panels in the link for convenient single-point communications. The 6700 also has a built-in, dual-line POTS and IP communicator with additional cellular options available.

The 6700 system can be enhanced by adding modules such as the 6860 remote annunciator which also has four programmable function buttons to help automate tasks and reduce time spent at the panel.

SWIFT® wireless compatibility provides options for wireless detection through a Class A mesh network. It is ideal for hard-to-wire locations, buildings where new wiring is not allowed, or to provide an easy install fire system for new construction projects. SWIFT devices can be combined with other hard-wired 6700 compatible devices. SWIFT is only compatible with System Sensor (SK) devices. It is not compatible with Hochiki (SD) devices.

The 6700 also has a form-C trouble relay, two programmable form-C relays, along with powerful features such as drift compensation, pre-trouble maintenance alert, a built-in sensor test to comply with NFPA 72 calibration testing requirements, and calibration trouble alert.



6700

The 6700 supports a variety of devices, including the 6860, 5860, and 6855 remote annunciators, 5824 serial parallel printer interface module (for printing system reports), the 5496 NAC expander, 5895XL power module, and SK or SD devices.

FEATURES & BENEFITS

- Capable of providing up to 100 points to satisfy smaller installation needs
- Connect up to 17 panels on one site with convenient single-point access using the SK-NIC Network Interface Card. Connected panels can have mixed compatible FACP models
- Convenient field-upgradeable firmware
- Built-in dual path POTS and IP communications with optional cellular models available for reliable backup reporting
- 6860 annunciator with a 4 x 40 large display
- Four user-programmable buttons minimize time spent executing complex or routine tasks
- Built-in USB interface for convenient and quick programming
- Programmable date setting for automatic and convenient Daylight Saving Time changes
- JumpStart® auto programming reduces installation time
- 125 software zones and 125 output groups for flexible design options

SIGNAL LINE CIRCUIT (SLC)

The 6700 SLC loops support multiple device types, maintenance alerts, and a built-in sensor test to comply with NFPA 72 calibration testing requirements.

INDICATOR LIGHTS

- **General Alarm (Red):** Flashes if in alarm; solid when alarm is silenced
- **Supervisory (Yellow):** Flashes if a supervisory condition exists; solid when supervisory is silenced
- **System Trouble (Yellow):** Flashes if a trouble condition exists; solid when trouble is silenced
- **System Silenced (Yellow):** On when an alarm, trouble or supervisory condition has been silenced but not yet cleared
- **System Power (Green):** Flashes for AC failure; solid when power systems are normal

USER INTERFACE

The 6700 built-in 4 x 20 annunciator with 80 character LCD display and large easy-to-use tactile touchpad can be used for system operation, programming and maintenance. It has five LEDs for alarm, supervisory, system trouble, system silenced and system power.

System operations include silencing alarms and troubles, resetting alarms and the display of alarm troubles and memory. The system's non-volatile event history buffer stores 1,000 events for viewing from the built-in or remote annunciator. System operations can be initiated with a mechanical firefighter's key or a valid 4- to 7-digit operator's code.

PROGRAMMING

The 6700 system offers several options to simplify and speed-up programming. JumpStart® auto programming minimizes programming required to start a new system. The built-in keypad, or the 6860, 5860 or 6855 remote annunciators give you on-site access to current system programming. Programming can also be accomplished using the Windows®-based Honeywell Fire Software Suite (HFSS) program.

SOFTWARE TOOLS

SKST: Silent Knight Selection Tool provides the installer or design architect with a Windows® software system configuration tool to create a detailed Bill of Material (BOM) and battery calculations.

HFSS: Honeywell Fire Software Suite provides communication and panel programming, detector status, event history and additional data. Requires a PC running Microsoft® Windows®.

ADDITIONAL INFORMATION

Twisted-unshielded pair wire is recommended. The 6700 also has 13 preset notification cadence patterns (including ANSI 3.41).

AGENCY LISTINGS AND APPROVALS

NPFA 13, NFPA 15, NFPA 16, NFPA 70, NFPA 72: Central station; remote Signaling; Local Protective Signaling Systems; Auxiliary Protected Premises Unit; Water Deluge releasing service. Suitable for automatic, manual, waterflow, sprinkler supervisory (DACT non-coded) signaling services

- **UL Listed:** S2766
- **CSFM** 7165-0559:0501
- **FDNY COA#** 6250

ORDERING INFORMATION

6700: Addressable Fire Alarm Control Panel. (Red cabinet)

COMPATIBLE ANNUNCIATORS

6860: 4x40 LCD remote fire annunciator (4 lines and up to 160 characters) per system; four programmable buttons

5860: 4x20 LCD remote fire annunciator. 5860 is gray; 5860R is red

6855: 4x20 LCD remote fire annunciator

5865-3 or 5865-4: LED annunciators can display up to 30 LEDs (15 red and 15 yellow). The 5865-4 has key switches for silence and reset, and a system trouble LED.

5880: The 5880 LED / IO module has 40 programmable LED outputs and eight supervised dry contact inputs which are useful for custom applications. You can use up to eight 5880 modules on one control panel for maximum flexibility. Its compact size allows mounting inside the annunciator, or in an accessory cabinet.

6700 COMPATIBLE DEVICES AND ACCESSORIES

See the data sheets listed below for a complete listing of the SK, SD or SWIFT devices.

53623: SK Devices Data Sheet

53624: SD Devices Data Sheet

350614, 350616 & 350618: SWIFT wireless devices

For a complete and current listing of compatible devices and accessories, visit

www.silentknight.com

Important: You cannot mix SK and SD devices in the same fire alarm system.

SK COMPATIBLE ADDRESSABLE DEVICES

SK-ACCLIMATE: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature

SK-BEAM: Reflected beam smoke detector without test feature

SK-BEAM-T: Reflected beam smoke detector with test feature

SK-CONTROL: Supervised control module

SK-CONTROL-6: Six circuit supervised control module

SK-DUCT: Photoelectric duct smoke detector with extended air speed range

SK-FIRE-CO: Four criteria fire and carbon monoxide detector

SK-HEAT: Fixed thermal detector (135°F)

SK-HEAT-W: Fixed thermal detector (135°F), white

SK-HEAT-ROR: Fixed rate of rise detector (135°F)

SK-HEAT-ROR-W: Fixed rate of rise detector (135°F), white

SK-HEAT-HT: Fixed high temperature thermal detector (190°F)

SK-HEAT-HT-W: Fixed high temperature thermal detector (190°F), white

SK-ISO: Fault isolator module

SK-MINIMON: Mini monitor module

SK-MONITOR: Monitor module

SK-MONITOR-2: Dual input monitor module

SK-MON-10: 10 input monitor module

SK-PHOTO: Photoelectric smoke detector

SK-PHOTO-W: Photoelectric smoke detector, white

SK-PHOTO-T: Photoelectric smoke detector with thermal (135°F fixed temperature)

SK-PHOTO-T-W: Photoelectric smoke detector with thermal (135°F fixed temperature), white

SK-PHOTOR: Photoelectric detector with remote test capability

SK-PHOTO-R-W: Photoelectric detector with remote test capability, white

SK-PULL-SA: Addressable single action pull station

SK-PULL-DA: Addressable dual action pull station

SK-RELAY: Addressable relay module

SK-RELAY-6: Addressable Six relay control module

SK-RELAYMON-2: Addressable Dual relay/monitor module

SK-ZONE: Addressable zone interface module

SK-ZONE-6: Six zone interface module

B300-6(-IV): 6" base for SK-W Series

B210LP: 6" mounting base

B501(-BL,-IV,-WHITE): 4" flangeless base

B501: 4" Flangeless mounting base

B200S(-IV,-WH): Intelligent sounder base

B200S: Intelligent sounder base

B200S-LF(-IV,-WH): Low-Frequency intelligent sounder base

B200S-LF: Low-frequency intelligent sounder base

B224RB(-IV,-WH): Relay base

B224RB: Relay base

B224BI(-IV,-WH): Isolator base

B224BI: Isolator base

SD COMPATIBLE ADDRESSABLE DEVICES

SD505-6AB: Addressable 6" base

SD505-6IB: Addressable 6" short circuit isolator base

SD505-6RB: Addressable 6" relay base

SD505-6SB: Addressable 6" sounder base

SD500-AIM: Addressable input module (switch input)

SD500-ANM: Addressable notification module

SD500-ARM: Addressable relay module

SD505-DTS-K: Remote test switch and LED indicator for the SD505-DUCTR

SD505-DUCT: Addressable Duct Smoke Detector.

SD505-DUCTR: Addressable Duct Detector housing with relay base.

SD505-HEAT: Absolute temperature heat detector. Trip point range from 135°F–150°F (0°C–37°C).

SD500-LIM: Addressable Line isolator module

SD500-MIM: Addressable Mini input monitor module (switch input)

SD505-PHOTO: Photoelectric smoke detector

SD500-PS/-PSDA: Addressable Single or dual action pull station

SD500-SDM: Addressable smoke detector module

AUDIBLE/VISIBLE DEVICES

These AV devices are all 2-wire. Color: "R" indicates red; "W" denotes white. For a complete listing of Silent Knight AV devices go to www.silentknight.com.

CHSRL/CHSWL: Wall chime/strobe

CHSRL/CHSCWL: Ceiling chime/strobe

CHRL/CHWL: Wall chime

HRL/HWL: Wall horn

P2RL/P2WL: Wall horn/strobe

PC2RL/PC2WL: Ceiling horn/strobe

SRL/SWL: Wall strobe

SCRL/SCWL: Ceiling strobe

SPSRL/SPSCWL: Ceiling speaker/strobe

SPSRL/SPSWL: Wall speaker/strobe

SPRL/SPWL: Wall speaker

SPCRL/SPCWL: Ceiling speaker

SWIFT WIRELESS DEVICES

SWIFT is only compatible with System Sensor (SK) devices. It is not compatible with Hochiki (SD) devices.

WSK-WGI: Wireless Gateway

WSK-PHOTO: Wireless Photoelectric smoke detector

WSK-PHOTO-T: Wireless Multi-criteria photoelectric smoke detector with thermal detection (135°F fixed temperature) and B510W 4" base

WSK-HEAT: Wireless Heat, (135°F fixed temperature) and B510W 4" base

WSK-HEAT-ROR: Wireless heat, ROR (135°F fixed temperature) and B510W 4" base

WSK-MONITOR: Wireless monitor module

WSK-RELAY: Wireless relay module

W-USB: SWIFT Tools USB transceiver used for communication with SWIFT devices

SBUS ACCESSORIES

5496: A 6 amp notification power expander with four power-limited notification appliance circuit outputs.

5883: Relay interface. Provides 10 Form C relays.

5824: Serial/Parallel printer interface module for printer connection.

5895XL: Power supply with six Flexput® circuits, and two Form C relays. Max. 16 per system.

5815RMK: Remote mounting kit. Dimensions 10 3/8"W x 10-3/16"H x 3"D

COMMUNICATION OPTIONS

CELL-CAB-SK: Cellular communicator, metal enclosure with lock/key*

CELL-MOD: Cellular communicator, plastic enclosure*

*Sole path, powered by panel.

IPGSM-4G: Dual path fire alarm communicator, cellular and/or IP (primary or backup, selectable)

SK-IP-2: Remote reporting via the Internet. Requires a VisorAlarm® receiver at the central station

MISC. ACCESSORIES

SK-NIC: Network Interface Card. Provides a common communications link for the 6700

SK-NIC-KIT: Installation Accessory Kit

SK-FML: Fiber-Optic Multi Mode, transmitter and receiver

SK-FSL: Fiber-Optic Single Mode

RBB: Remote battery box accessory cabinet for batteries that are too large to fit in the FACP cabinet. Dimensions: 16" W x 10" H x 6" D (406mm W x 254mm H x 152mm D).

SK-SCK: Seismic Compliance Kit used to securely fasten batteries to the fire panel.

6700 Technical Specifications

PHYSICAL

Overall Dimensions: 12.71" W x 15.12" H x 3.33" D

Weight: 15 lbs.

Color: Red

ENVIRONMENTAL

Operating Temperature: 32°F to 120°F (0°C to 49°C)

Humidity: 0 to 93% relative humidity (non-condensing)

ELECTRICAL

6700 Primary AC: 120 VAC @ 60 Hz, 1.5A Total

Accessory Load: 2.5A @ 27.4 VDC power-limited

Standby Current: 165mA

Alarm Current: 310mA

Battery Charging Capacity: 7 to 35AH

Battery Size: 7AH max. allowed in control panel cabinet. Larger capacity batteries can be housed in RBB accessory cabinet.

NOTIFICATION APPLIANCE CIRCUITS (NACs)

Two programmable circuits which can be programmed individually as:

NACs: 2.5A @ 27.4VDC per circuit, power-limited (with a panel maximum current of 2.5A)

Auxiliary Power Circuits: 2.5A @ 27.4VDC per circuit, power-limited

Supports Class B (Style 4) and Class A (Style 6 or 7) configuration for the SLC

WIRING: See the product manual for wiring details

Flexput®, Honeywell®, JumpStart®, Silent Knight®, SWIFT®, and System Sensor® are registered trademarks of Honeywell International Inc.

Hochiki® is a registered trademark of Hochiki Corporation. Microsoft® and Windows® are registered trademarks of Microsoft Corporation.

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

For Technical Support, call 800-446-6444.

Honeywell Silent Knight

12 Clintonville Road
Northford, CT 06472
800-328-0103

www.silentknight.com

351607 | B | 09/18
© 2018 Honeywell International Inc.

